

PowerZone Connect

1002-1502-2004-3004



BLAZE

About PowerZone Connect

- ✔ **More Power. Still Connected** – 2U, full rack. Next level power with 2 and 4 channels – up to 3000 W total system power for bigger installs and larger locations.
- ✔ A powerful extension to the PowerZone connect series of **full matrix DSP** amplifiers with the same set-up and configuration via the same PowerZone Control web app.
- ✔ Connect via the amps **Wi-Fi**, or direct via the **network port**. Use any device and any browser. Even set-up from your phone.
- ✔ Connect to the system with **PowerZone Control** – configure the complete system - input sources & output channels, set up sound Zones, EQ, routing and more.
- ✔ **Smart & connected** - means you can update new features with downloadable firmware updates, **install speaker EQ** files, back up and restore the system settings.
- ✔ **GPIO interface** enables adding of any standard remote control (potentiometer) or connect to smart automation controllers with our **3rd Party drivers**.
- ✔ **Link multiple amps** – via S/PDIF (Master /Slave)
- ✔ Pascal's UMAC Class D amplifier technology is inside, with market proven, **ultra-reliable** amplifier modules.

Model specifications



Model	Total Power	Power @ 2 Ω	Power @ 4Ω	Power @ 8Ω	Power @ 70V	Power @ 100V
PowerZone Connect 1002	1000 W	2x500 W (SE)	2x500 W (SE) 1x1000 W (BTL)	2x250 W (SE) 1x1000 W (BTL)	1x1000 W (BTL)	1x1000 W (BTL)
PowerZone Connect 1502	1500 W	2x750 W (SE)	2x750 W (SE) 1x1500 W (BTL)	2x400 W (SE) 1x1500 W (BTL)	1x1200 W (BTL)	1x1500 W (BTL)
PowerZone Connect 2004	2000 W	4x500 W (SE)	4x500 W (SE) 2x1000 W (BTL)	4x250 W (SE) 2x1000 W (BTL)	2x1000 W (BTL)	2x1000 W (BTL)
PowerZone Connect 3004	3000 W	4x750 W (SE)	4x750 W (SE) 2x1500 W (BTL)	4x400 W (SE) 2x1500 W (BTL)	2x1200 W (BTL)	2x1500 W (BTL)